


Belmont

Category: Belmont


Part Number: 430242-80

Description: Belmont Linear High Bay 180W 5000K IP66 Grey
25x80D



Product Features:

- Fresnel optics for improved glare control
- Tough, impact resistant IK10 housing
- Plug & Play Enabled – Sensors and Emergency





General information:

Wattage (W)	180
Lumens (lm)	27925
Efficacy (lm/W)	155
Beam Angle	25x80
CRI	80
Colour Temperature (K)	5000
Operating Temperature From	-30
Operating Temperature To	50
Application Location	Internal

Technical information:

Class Rating	1
Input Type	220-240V AC
IP Rating	66
IK Rating	10
L70 Hours	50000
L80 Hours	0
L90 Hours	0
Product Warranty (Years)	5
SDCM	0
Surge (kV)	6 L-N 6 L / N-G




Belmont

Category: Belmont

Part Number: 430242-80

Description: Belmont Linear High Bay 180W 5000K IP66 Grey
25x80D



Compatible Products:



401754

Alwen PIR Highbay Remote



430569

Alwen Plug & Play 12V
Microwave Sensor 12M Black
(Zhaga)



430568

Alwen Plug & Play 12V PIR
Sensor Black (Zhaga)



430243

Belmont +/- 60D Rotatable
Bracket (Pair)



430964

Grafham 4W E-SEL3 Linear
High Bay Emergency
Conversion Pack 20-55V DC
100mA LifePO4 6.4V DC
3.3Ah Plug & Play



430625

truSmart Crown Zhaga Plug &
Play 12V PIR Sensor Black